

LED EMERGENCY LIGHT

(Indoor / Outdoor Emergency)



The Energywise Emergency LED Light may be placed on walls or ceilings near exit locations, and can be combined with our Emergency EXIT Signs for a great EXIT sign combination. With a nickel cadmium battery, the charging time for this fixture is 24 hours, with a discharge time or backup time of 90 minutes.



SPECIFICATIONS

PART #	EWENLED-EMLT
SIZE	13.36" X 3.73" X 4.52"
FIXTURE COLOR	WHITE
WATTAGE	3.5 W
INPUT VOLTAGE	120V - 277V
LUMENS	180 LM
DIMMING	NON-DIMMABLE
CCT	5000K
BATTERY BACKUP	STANDARD
ENVIRONMENT	OPTIONAL DAMP LOCATION RATED
LIFESPAN	> 50,000 HOURS
WARRANTY	3 YEARS
BEAM ANGLE	180 DEGREES
MOUNTING	WALL / CEILING